

**Use of any dimmers, switches, or other control not from the list below may damage the fixture and void warranty**

AL-3162 Triac/Phase-cut dimmers										
Brand	Type	Series	Model #	Wiring	watts	dimming method	Version Code	Max # of Luminaires	Notes	minimum dimming range
Lutron	C.L	Ariadni/Toggler C.L	AYCL-153P	Single-pole/3-way	150	Toggler	T8, T9	7	3-Way only works with a 3-Way switch	0%
			TGCL-153P							
			Diva C.L							
			Skylark C.L							
			Skylark Contour C.L							
		Lumea C.L	LGCL-153P							
		Maestro C.L	MACL-153M	Single-pole/3-way/ multi-location	150	Digital	2014	7	3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R	3%
			M_SCL-VP153M	Single-pole/3-way/ multi-location	150	Digital/Vacancy Sensor	T2	7	3-Way only works with a 3-Way switch or dimmer companion MA-R (not a dimmer). Multi-location only work with MA-R	3%
			M_SCL-OP153M	Single-pole/3-way/ multi-location	150	Digital/Occupancy Sensor				
			MRF2-6CL	Single-pole/3-way/ multi-location	150	Digital and Wireless	M6	7	3-Way or multi-location only works with companion MA-R (not a dimmer)	5%
Nova T	NTCL-250	Single-pole	250	slide to off	BR Y02	12		3%		
Grafik T	GT-150	Single-pole/3-way/ multi-location	150	Digital	T6	7	3-Way or multi-location only works with companion GT-AD (not a dimmer)	2%		
RF C.L	Grafik T RF	GTJ 150			M6			2%		
Leviton	Universal Dimmer	Decora	DSL06-1L	Single-pole/3-Way	300	slide with ON/OFF button	NA	14	3-Way only works with a 3-Way switch	18%
		Illuma Tech	IPL06-10	Single-pole/3-Way	150	slide with ON/OFF button	NA	7	3-Way only works with a 3-Way switch	3%
		Sureslide	6672-1L	single	150	slide to off	NA	7		12%
		Sureslide	6674-P0	Single-pole/3-Way	150	slide with ON/OFF button	NA	7	3-Way only works with a 3-Way switch	3%
		Renu	REL06	Single-pole/3-Way	300	Digital	NA	14	3-Way only works with remote RE00R Requires neutral wire connection	9%
		Decora Digital	DDMX1-BL	Single-pole/3-Way	450	Digital or Bluetooth	NA	22	3-Way only works with remote DDOOR-DL Requires neutral wire connection	4%

